

DIVA P90 POWER AMPLIFIER

CONTINUOUS POWER OUTPUT PER CHANNEL

ALL CHANNELS 8Ω, 20HZ-20KHZ	90W
SINGLE CHANNEL 4Ω, 1KHZ	165W
DISTORTION 8Ω, 80% POWER, 1KHZ	0.008%

INPUTS

INPUT SENSITIVITY	700MV
INPUT IMPEDANCE	22KΩ
SIGNAL TO NOISE RATIO (CCIR)	112DB

GENERAL

POWER CONSUMPTION (MAXIMUM)	800VA
SIZE W/D/H MM. INC. FEET	435X340X100
WEIGHT (NET)	9.5KG

ALL SPECIFICATIONS SHOWN BELOW ARE TYPICAL, UNLESS OTHERWISE STATED. PLEASE NOTE THAT ARCAM'S POLICY IS ONE OF CONTINUOUS IMPROVEMENT. WE THEREFORE RESERVE THE RIGHT TO CHANGE THE MATERIAL, DIMENSIONS, SPECIFICATIONS OR DESIGN OF OUR PRODUCTS SHOWN OR REFERRED TO HEREIN AT ANY TIME AND WITHOUT PRIOR NOTICE. ILLUSTRATIONS USED IN OUR LEAFLETS ARE INTENDED AS A GUIDE ONLY. E&OE 06/04.

ARCAM IS A REGISTERED TRADEMARK OF A&R CAMBRIDGE LTD. 'DOLBY', 'DOLBY STEREO', 'DOLBY SURROUND' AND 'PRO LOGIC II' ARE TRADEMARKS OF DOLBY LABORATORIES LICENSING CORPORATION. DTS IS A TRADEMARK OF DTS CORPORATION. HDCD AND WMA ARE TRADEMARKS OF MICROSOFT CORPORATION.